



Horizontal Openwell (THREE PHASE)

HORIZONTAL OPENWELL SUBMERSIBLE PUMP SET (Suitable For well,River,Dam)

Approx Performance Chart at ,2800 Rpm,380 To 420 V (TP), 50Hz Ac supply

1.0HP OPENWELL (TP)

NO.	MOTOR BODY	THREE PHASE MODEL NO.	MOTOR HP	Outlet Inch	Head In METER & Discharge in LPM				SS BODY	CI BODY
					METER / LPM	METER / LPM	METER / LPM	METER / LPM		
25	V-7	JH11TP7	1.0	OPENX1"	14/180	20/155	24/125	30/60	✓	✗
26	V-7	JH115TP7	1.0	1.5"X1.5"	6/380	10/320	12/280	20/140	✓	✗
27	V-7	JH12TP7	1.0	2"X2"	4/526	9/414	11/365	16/180	✓	✗

1.5HP OPENWELL (TP)

28	V-7	JH1512TP7	1.5	1.5"X1.25"	14/255	21/220	27/132	30/70	✓	✗
29	V-7	JH1515TP7	1.5	1.5"X1.5"	7/365	15/340	17/285	25/130	✓	✗
30	V-7	JH152TP7	1.5	2"X2"	5/480	12/410	14/320	18/225	✓	✗

2.0HP OPENWELL (TP)

31	V-7	JH215TP7	2.0	OPENX1.5"	12/450	16/430	25/230	30/180	✓	✓
32	V-7	JH22TP7	2.0	OPENX2"	10/500	18/400	20/350	25/220	✓	✓
33	V-7	JH225TP7	2.0	2.5"X2.5"	5/700	10/620	12/430	18/100	✓	✓

3.0HP OPENWELL (TP)

34	V-7	JH32TP7	3.0	2.5"X2"	10/610	18/550	24/355	32/100	✓	✓
35	V-7	JH325TP7	3.0	2.5"X2.5"	11/710	16/660	22/410	28/180	✓	✓
36	V-9	JH32TP8	3.0	OPENX2"	12/610	18/450	28/400	36/200	✓	✗
37	V-9	JH325TP8	3.0	OPENX2.5"	10/780	15/690	22/550	28/220	✓	✗
38	V-9	JH32TP9	3.0	OPENX2"	20/730	24/650	32/330	36/210	✓	✓
39	V-9	☐RHH-2	3.0	OPENX2.5"	8/900	16/780	25/650	32/120	✓	✓
40	V-9	JH33TP9	3.0	OPENX3"	7/930	14/820	16/750	22/350	✓	✓

5.0HP OPENWELL (TP)

41	V-7	JH52TP7	5.0	2.5"X2"	14/600	26/450	32/250	35/120	✓	✓
42	V-7	JH525TP7	5.0	2.5"X2.5"	15/760	20/700	25/530	27/460	✓	✓
43	V-9	JH52TP8	5.0	OPENX2"	20/520	27/450	34/400	44/220	✓	✗
44	V-9	JH525TP8	5.0	OPENX2.5"	20/880	24/660	30/550	33/200	✓	✗
45	V-9	JH52TP9	5.0	OPENX2"	22/650	30/520	38/380	44/240	✓	✓
46	V-9	☐RHH-5	5.0	OPENX2.5"	18/920	22/750	30/670	36/250	✓	✓
47	V-9	JH53TP9	5.0	3"X3"	8/1250	12/1150	20/880	28/380	✓	✓
48	V-9	JH54TP9	5.0	4"X4"	6/1650	12/1400	15/1250	18/800	✓	✓



Horizontal Openwell (THREE PHASE)

HORIZONTAL OPENWELL SUBMERSIBLE PUMP SET (Suitable For well,River,Dam)

Approx Performance Chart at ,2800 Rpm,380 To 420 V (TP), 50Hz Ac supply.

6.0HP OPENWELL (TP)

NO.	MOTOR BODY	THREE PHASE MODEL NO.	MOTOR HP	Outlet Inch	Head In METER & Discharge in LPM				SS BODY	CI BODY
					METER / LPM	METER / LPM	METER / LPM	METER / LPM		
49	V-9	JH62TP9	6.0	OPENX2"	25/620	30/580	37/490	44/290	✓	✓
50	V-9	JH625TP9	6.0	OPENX2.5"	17/1150	22/980	30/610	32/200	✓	✓
51	V-9	JH63TP9	6.0	OPENX3"	10/1240	15/1100	22/990	30/320	✓	✓
52	V-9	JH64TP9	6.0	4"X4"	5/1810	12/1500	18/1120	24/380	✓	✓

7.5HP OPENWELL (TP)

53	V-9	JH752TP9	7.5	OPENX2"	30/680	40/580	45/480	55/120	✓	✓
54	V-9	☒RHH-15	7.5	OPENX2.5"	25/1050	30/990	35/880	40/200	✓	✓
55	V-9	JH7525TP9	7.5	2.5"X2.5"	22/950	35/840	40/700	50/330	✓	✓
56	V-9	JH753TP9	7.5	3"X3"	20/1400	24/1350	28/1180	35/550	✓	✓
57	V-9	JH754TP9	7.5	4"X4"	15/1800	20/1550	23/1250	30/600	✓	✓

10.0HP OPENWELL (TP)

58	V-9	JH102TP9	10.0	2.5"X2"	30/1050	44/540	50/520	57/230	✓	✓
59	V-9	☒RHH-20	10.0	2.5"X2.5"	30/1120	34/1050	42/850	50/500	✓	✓
60	V-9	JH103TP9	10.0	3"X3"	22/1400	26/1280	32/1100	38/600	✓	✓
61	V-9	JH104TP9	10.0	4"X4"	15/2000	20/1800	24/1500	34/550	✓	✓

12.5HP OPENWELL (TP)

62	V-9	JH1225TP9	12.0	2.5"X2.5"	24/1470	40/1020	50/780	58/180	✓	✓
63	V-9	JH124TP9	12.0	4"X4"	15/2400	20/2250	28/1600	34/1100	✓	✓

15.0HP OPENWELL (TP)

64	V-9	JH1525TP9	15.0	2.5"X2.5"	26/1480	30/1350	50/990	60/470	✓	✓
65	V-9	JH154TP9	15.0	4"X4"	18/2680	22/2480	30/1880	38/1180	✓	✓

20.0HP OPENWELL (TP)

66	V-9	JH2025TP9	20.0	2.5"X2.5"	40/1020	50/950	60/900	80/150	✓	✓
67	V-9	JH204TP9	20.0	4"X4"	18/2880	20/2600	28/2200	40/1200	✓	✓

